

# innovason

## Quick guide to update M.A.R.S software.

- 1 – Upload the “package” file from our Website (\*.pak)
- 2 – Put the file in a USB key.
- 3 – From the “Project Manager”, click on “Administration”
- 4 – Enter User : admin, and Password : admin
- 5 – On the Left menu, press on the “Update” button.
- 5 – You are Now on this screen :

The screenshot displays the 'MT128 Administration Pages' interface. On the left is a vertical menu with buttons for 'General', 'Startup', 'Other Options', 'Server', 'Licensing', 'Update' (highlighted), 'Script (Keyboard required)', 'System (administration)', and 'Exit'. The main area is titled 'Update Path (where to select package):' and shows a file explorer view of a USB drive 'K:\'. A green arrow points from a callout box to the 'K:\' path. The file list contains four .pak files: 'MT128\_V1\_0\_7\_1.pak', 'MT128\_V1\_0\_7\_0.pak', 'MT128\_V1\_0\_6\_5.pak', and 'MT128\_V1\_0\_6\_0.pak'. Below the file list is a 'Load Package' button. Underneath, the 'Previous Installed Version:' section lists four versions with their installation dates and times. At the bottom right is an 'Activate Version' button.

**1) Click here to select your USB Key**  
**2) Select the folder containing the .pak file.**

Version	Installation date
Version: 1,0,7,1	Installation date : 01/27/2010 - 11:25 (US) This version is launched on startup
Version: 1,0,7,0	Installation date : 01/03/2010 - 16:09 (US)
Version: 1,0,6,10	Installation date : 12/22/2009 - 13:12 (US)
Version: 1,0,6,5	Installation date : 09/09/2009 - 07:41 (US)

## Package Installation

Package filename: **MT128\_V1\_0\_7\_1.pak**

Installation Name: **MT128**

Integration Name: **MT128 Standard**

Main Vendor Name: **Integrators**

Product Version: **1,0,7,1**

Comment/Information about the package:

- ASIO MOTOR : Audio Conversion supplied : ASIOStInt24MSB.
- Small problem of display in the DiskManager page.
- ESC : In some cases , typing ESC in the startup page was causing MT128 shutdown.
- SYS SET : Bug in MIDI list selector when there is no MIDI device installed on the system.

**Start Installation**

(Installation will take effect on next launch)

**Cancel**

- 3) Start the installation of the Package
- 4) When asked, reboot the computer. Done.

Note : please be aware that the previous versions are style available and it is up to you to decide which version to activate for your sessions.

